
Name_


April 7, 2003

MAE 311 Machines and Mechanisms I Two 8 1/2 sheets of notes and a calculator are permitted Time: 50 minutes Test 2

1. A C-shaped clamping device, shown below, is to be made of 50 mm wide plate and is loaded by a force, F, that fluctuates between 0 to 60 kN. What should be the thickness, b, of the clamp in order to provide a factor of 4 for an infinite life at point, P? Use a surface finish of 0.75 and a size factor of 0.87. The material (steel) has an ultimate strength of 0.5 GPa. The area moment of inertia is bh³/12 where h is the width. Also, the maximum bending stress is Mc/I. (35 pts.)



2. The hydraulic cylinder shown below is held together by four 3/8 inch diameter SAE grade 5 coarse bolts with a proof strength of 85kpsi. The tensile area is 0.078 square inches. They are tightened to a preload of 75% of the proof load. The stiffness of each bolts is 0.245 Mlb/in and the cylinder has a total stiffness of 10 Mlb/in. Will the bolts fail or will the joints separate first? Justify your answer. (Assume the end plates to be



3. A nested two-spring arrangement is shown below. The outer spring has a wire diameter of 2mm and an outside diameter of 22mm. The inner spring has a 1.4mm wire diameter and a 15.4 mm outside diameter. Both springs have 16 coils and are made of steel with a shear modulus of 80 GPa. Which spring sees the higher shear stress? (Note that both springs undergo identical deflections.)(35 pts).

that both springs undergo identical deflections (135 pts).

$$C_0 = \begin{pmatrix} D \\ d \end{pmatrix} = \begin{pmatrix} 22-2 \\ 2 \end{pmatrix} = 10 \cdot \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20 \\ D_0 = 20 \end{pmatrix}$$

$$K_S = \frac{1}{12} = \begin{pmatrix} D_0 = 20$$