
MAE334 - Introduction to Instrumentation and Computers

Midterm Examination

October 29, 2008



The terms *lab 1, lab 2*, and *lab 3* refer to: Lab 1 Static and Dynamic Calibration of Thermocouples and Lab 2 Basics of A to D Conversion and Lab 3 Transient Thermal Behavior with Work and Heat Loss.

All multiple choice questions are worth 2 points.

All short answer questions are worth 5 points.

Total 25x2 + 6x5 = (80 points) midterm + Quizzes (20 points)

	a. 0.70 d. 4.0 b. 0.25 (e. 1.5 c. 1.05
3.	Of the two second order system responses plotted in Figure 1 which system has the largest damping ratio, ζ. a. response (a) b. response (b)
	The damped natural frequency, ω_d , of response (a) is higher than that of response (b) of the second order systems plotted in Figure 1. (a) True b. False
5.	The value of the integral of the delta function over the interval from $t = -\infty$ to -1, $A = \int \delta(t)dt$, is
	a. ∞ b. 1
6.	The discrete Fourier transform of a signal sampled once every hundredth of a second ($\delta t = 1/100$ sec) for 5 seconds would have a maximum frequency of a. 100 Hz a. 100 Hz b. 1/10 Hz c. None of the above c. 1/5 Hz
7.	What is the equation relating the confidence interval that a single temperature measurement, T_i , is within 5% of the mean if the data set contains 36 points and has a standard deviation of 1 °C?
	a. $T_i = T' \pm t_{35,95\%} / \sqrt{36}$ c. $T_i = T' \pm t_{35,5\%} / \sqrt{36}$ e. None of the above
	b. $T_{\rm i}=\overline{T}\pm t_{35,95\%}1$
8.	A discrete Fourier transform of the data plotted in Figure 1 would have a frequency spacing, df, of a. 4 Hz d. 2 Hz e. None of the above $Af = \frac{1}{T} = \frac{1}{45eC} = 0.25 \text{ Hz}$ e. None of the above
9.	What sampling rate would be required to accurately represent the wave form shape of the second order system response function plotted in Figure 1? At least 10 times the highest frequency a. 1 Hz b. 2 Hz c. 4 Hz
10	. Heat loss to the laboratory surroundings from the calorimeter used in lab 3 was modeled with the equation, $Q = H(T_{calorimeter} - T_{lab})$ a True b. False

1. An instrument's precision is a measure of the random fluctuations in output for repeated applications of the same input.

2. The settling time in seconds of the second order system response (a) plotted in Figure 1is

b. False

(a.) True

approximately

MAE 334 - Midterm Exam, October 29, 2008

2 of 6

a. 1 volt (c.) 0.25 volts ($\sqrt{\frac{4}{2}}$) e. None of the b. 0.5 volts (d. 0.125 volts) ($\sqrt{\frac{4}{2}}$) $\sqrt{\frac{4}{2}}$	above	Э			
12. A very small, very sensitive thermocouple will reach a steady state value sooner to input than a large step input. a. True (b) False	or a s	mall	step)	
13. The ADC architecture normally associated with the highest precision and slowest is	conv	ersio	n ra	te	
a. Flash c. Successive Approximation b. Pipelined (d.)Sigma-Delta					
14. Randomization is used to break-up the effects of interference from either continuous extraneous (i.e. uncontrolled) variables. a.) True b. False	ous or	disc	rete		
15. The fundamental frequency of the Fourier series $y(t) = \sum_{n=1}^{\infty} \frac{3n}{2} \sin nt + \frac{5n}{3} \cos nt$ is					
a. 1 Hz d. 3/2 rad/sec e. None of the above c. 3/2 Hz					
16. When modeling the dynamic response of the thermocouple probe to a step input change in temperature only the initial temperature and the time constant are used. a. True b. False Also need a had temp or step size					
17. The time constant of the thermocouple plotted in Figure 2 is approximately a. 12 seconds. b. 5 seconds. d) 2 seconds					
18. What portion of the repeated sampling of a static temperature signal are within two standard deviations of the data set's mean value? a) 68.3% c. 95.5% b. 99.7% d. 50% e. None of the above					
19. What is the approximate variance of the data set whose probability density function Figure 3? a. 1 b. 2 e. 6 c. 3	n is p	lotte	d in		
20. What is the twos complement binary representation of -11 as an 8 bit number? $2^7 2^6 2^5 2^4$	$\frac{2^3}{l}$	2^2	21	2^0	
an 8 bit number? a. 10001011 b. 00001011 c. 11110100 d. 11110111 Per none of the above	0	0	0	0	
c. 11110100 Add 1		,		' /	
d. 11110111 2/5 (omp→ 1/1/1/1/1) € none of the above	U	/	0	_/_	

11. A 4 bit ADC with an input range of 16 volts and an input signal gain of 4 has a quantization step

21. What are the units of the static sensitivity of the thermocouple calibrated in the first lab used to convert the ADC output to temperature? a. Volts/C° b. milliVolts/C° c. C°/microVolts e. None of the above
 22. The frequency bandwidth of a first order instrument is defined as the frequency below which M(ω)=0.707, or output/input power is -3 dB. True b. False
23. The smallest quantization step size, as plotted in Figure 4, of the ADC used in the lab is? (a) 24.4 micro-Volts (b) 2.44 milli-Volts (c) 4.88 x 10 ⁻⁵ Volts
24. The polynomial equation, $y(x) = a_0 + a_1x + a_2x^2 + a_3x^3$, fit to a data set with 25 points has how many degrees of freedom? a 21' b. 22 c. 23 e. None of the above
25. It can be determined from the probability density function plotted in Figure 3 that the maximum allowable gain used by the ADC in the lab to collect this data would be? a 1 c. 20 ADC range is LIVV dis, data range is to be 2.
26. What is the equation used to calculate the damped or ringing frequency, ω_d , of an under damped second order sensor like the one plotted in Figure 1 in terms of natural frequency, ω_n , and the damping ratio, ζ ?
27. What is ADC quantization step size as defined in terms of the input range, E_{FSR} , $Gain$ and the number of ADC bits, M , for the ADC hardware in the lab with the maximum gain? $Q = \frac{20 \text{ Volts}}{400} / 2^{M} = \frac{20 \text{ Volts}}{400} / 2^{M}$
28. What is the equation used to find the standard deviation of a data set?
29. Given a data set with 20 points what is the equation used to find the confidence interval within which 95% of the data is expected to lie? \(\chi_1 = \frac{1}{2} \chi_1 \chi_2 \chi_3 \chi_4 \chi_1 \chi_2 \chi_3 \chi_4 \chi_1 \chi_1 \chi_2 \chi_3 \chi_4 \chi_1 \chi_1 \chi_1 \chi_2 \chi_1 \c
30. What is the 50% confidence interval of a linear fit $y = a_0 + a_1 x \pm CI$ to a 10 point data set?
31. What is the equation for the error function, Γ(t), used in lab 3 to linearize the cooling data to determine the calorimeter time constant?




Figure 1. Second order system response to a 2 unit step input function.




Figure 2. Thermocouple response to a 6 degree C step input temperature change.




Figure 3. Probability density function of a normally distributed data set.




Figure 4. Sample data collected during lab 2 with simulated data superimposed on plot.